

**PAGE 1/11** 

TITLE	DOC No.	DTRX-180017
	<b>REVISION:</b>	<b>AUTHORIZED BY:</b>
1G SFP SX Transceiver	04	Mike Sun
	DATE:	CLASSIFICATION:
	2022.05.26	Optical Transceiver



#### SFP 1G SX Transceiver

### 1. SCOPE

The scope of this specification is the definition of a high performance, cost effective modules, which is optimized for 1000BASE-SX, and transmission distance up to 550m. The transceiver consists of two sections: The transmitter section incorporates an 850nm VCSEL driver. The receiver section consists of a PIN photodiode integrated with a transimpedance preamplifier (TIA). The module is hot pluggable into the 20-pin connector.

### 2. PRODUCT DESCRIPTION

#### 2.1 PRODUCT NAME AND SERIES NUMBER(S)

#### SFP 1G SX Transceiver


Part Number	Data Rate	Wavelength (nm)	Distance	Media	Power (dBm)	Sen. (dBm)	Connector	Tem.
P58000ABCA01-1	1G	850	550m	MMF	-9.5 ~ -3	-17	LC	С
P58000ABIA01-1	1G	850	550m	MMF	-9.5 ~ -3	-17	LC	I



#### **PAGE 2/11**

TITLE	DOC No.	DTRX-180017
	<b>REVISION:</b>	AUTHORIZED BY:
1G SFP SX Transceiver	04	Mike Sun
	DATE:	CLASSIFICATION:
	2022.05.26	Optical Transceiver

#### 2.2 DIMENSIONS, MATERIALS, PLATINGS AND MARKING



### 3. APPLICABLE DOCUMENTS AND SPECIFICATIONS

- Compliant with SFP MSA
- Compliant with IEEE802.3z Gigabit Ethernet
- Compliant with SFF-8472 v9.3
- TUV certification

### 4. Regulatory Compliance

JPC transceivers are Class 1 Laser Products and comply with US FDA regulations. These products are certified by TÜV and CSA to meet the Class 1 eye safety requirements of IEC 60825-1 and IEC 60825-2. Copies of certificates are available at JPC Corporation upon request



**PAGE 3/11** 

TITLE	DOC No.	DTRX-180017
	<b>REVISION:</b>	AUTHORIZED BY:
1G SFP SX Transceiver	04	Mike Sun
	DATE:	CLASSIFICATION:
	2022.05.26	Optical Transceiver

### 5. Absolute Maximum Ratings & Recommended Operating Conditions

Absolute Maximum Ratings							
Parameter	Symbol	Min.	Max.	Unit			
Storage Temperature	Ts	-40	+85	℃ •			
Supply Voltage	V <sub>CC3</sub>	-0.5	4	V			
Relative Humidity(Non-condensing)	RH	5	95	%			
RX Input Average Power	Pmax	-	-3	dBm			

Recommended Operating Conditions							
Parameter	Symbol	Min.	Typical	Max.	Unit		
Operating Case Temperature(I-temp)	Tı	-40		85	$^{\circ}$ C		
Operating Case Temperature(C-temp)	T <sub>C</sub>	0		70	$^{\circ}\mathbb{C}$		
Power Supply Voltage	V <sub>CC3</sub>	3.135	3.3	3.465	V		
Data Rate			1.25/1.0625		Gbps		

Transmitter Operating Characteristic-Optical, Electrical							
Parameter	Symbol	Min.	Typical	Max.	Unit	Note	
Center Wavelength Range	λ <sub>C</sub>	830	850	860	nm	VCSEL LD	
Optical Power	Ро	-9.5	-6.5	-3	dBm	850nm VCSEL-LD	
Spectral width	Δλ			0.85	nm	VCSEL LD	
Extinction Ratio	ER	9	12	-	dB		
Relative Intensity Noise	RIN		_	-120	dB/Hz		
Eye Diagram	Complies with IEEE802.3z eye masks when filtered						
Optical Rise/Fall Time	Trise/Tfall			260	Ps		



**PAGE 4/11** 

TITLE	DOC No.	DTRX-180017
	<b>REVISION:</b>	AUTHORIZED BY:
1G SFP SX Transceiver	04	Mike Sun
	DATE:	CLASSIFICATION:
	2022.05.26	Optical Transceiver

Receiver Operating Characteristic-Optical, Electrical						
Parameter	Symbol	Min.	Тур.	Max.	Unit	Note
Receiver Sensitivity	S			-17	dBm	550m
Overload		0			dBm	
LOS	Optical Dessert			-21	dBm	
	Optical Dessert			-21	dBm	, Č
LOS	Optical Assert	-35			dBm	"78,
LOS Hysteresis		0.5		5	dB	

#### Notes:

[1] Receiver sensitivity is informative and shall be measured with conformance test signal for BER =1x  $10^{-12}$ .


Control and Status I/O Timing Charac		)			
Parameter	Symbol	Min.	Max.	Unit	Note
	Electrical (	Characteris	stics		
Supply current			300	mA	70.
Single Ended Data Input Swing		500	2400	mV	
Single Ended Data Output Swing		370	2000	mV	
TV foult /I OC output /TTI )	VOH	2.0	Vcc		
TX_fault /LOS output (TTL)	VOL	0	0.8	V	
TV disable input (TTI)	VOH	2.0	Vcc		
TX_disable input (TTL)	VOL	0	0.8	V	

## 6. Applications Note:



#### **PAGE 5/11**

TITLE	DOC No.	DTRX-180017
1G SFP SX Transceiver	<b>REVISION:</b>	AUTHORIZED BY:
	04	Mike Sun
	DATE:	CLASSIFICATION:
	2022.05.26	Optical Transceiver



#### Pin Definitions

#### Pin Assignment

Pin	Logic	Symbol	Name/Description	Note
1		VeeT	Module Transmitter Ground	1
2	LVTTL-O	TX_Fault	Module Transmitter Fault	3
3	LVTTL-I	TX_Disable	Transmitter Disable; Turns off transmitter laser output	3
4	LVTTL-I/O	SDA	2-wire Serial Interface Data Line (Same as MOD-DEF2 as defined in the INF-8074i)	3
5	LVTTL-I/O	SCL	2-wire Serial Interface Clock (Same as MOD-DEF1 as defined in the INF-8074i)	3
6		MOD_ABS	Module Absent, connected to VeeT or VeeR in the module	3
7	LVTTL-I	RS	Rate select, optionally controls SFP module receiver. When High input data rate 10.3GBd and when LOW data-rate 1.25GBd.	3
8	LVTTL-O	RX_LOS	Receiver Loss of Signal Indication (In FC designated as RX_LOS, in SONET designated as LOS, and in Ethernet designated at Signal Detect)	3
9		VeeR	Module Receiver Ground	1
10		VeeR	Module Receiver Ground	1



#### **PAGE 6/11**

TITLE	DOC No.	DTRX-180017
	<b>REVISION:</b>	<b>AUTHORIZED BY:</b>
1G SFP SX Transceiver	04	Mike Sun
	DATE:	CLASSIFICATION:
	2022.05.26	Optical Transceiver

11		VeeR	Module Receiver Ground	1
12	CML-O	RD-	Receiver Inverted Data Output	3
13	CML-O	RD+	Receiver Non-Inverted Data Output	3
14		VeeR	Module Receiver Ground	1
15		VccR	Module Receiver 3.3 V Supply	2
16		VccT	Module Transmitter 3.3 V Supply	2
17		VeeT	Module Transmitter Ground	1
18	CML-I	TD+	Transmitter Non-Inverted Data Input	3
19	CML-I	TD-	Transmitter Inverted Data Input	3
20		VeeT	Module Transmitter Ground	


#### Notes:

- 1. The module signal ground pins, VeeR and VeeT, shall be isolated from the module case.
- 2. This pin is an open collector/drain output pin and shall be pulled up with 4.7k-10kohms to Host\_Vcc on the host board. Pull ups can be connected to multiple power supplies, however the host board design shall ensure that no module pin has voltage exceeding module VccT/R + 0.5 V.
- 3. This pin is an open collector/drain input pin and shall be pulled up with 4.7k-10kohms to VccT in the module.



**PAGE 7/11** 

TITLE	DOC No.	DTRX-180017
	<b>REVISION:</b>	<b>AUTHORIZED BY:</b>
1G SFP SX Transceiver	04	Mike Sun
	DATE:	CLASSIFICATION:
	2022.05.26	Optical Transceiver



**Block Diagram of Transceiver** 

#### **Transmitter Section**

The transmitter converts 1.25Gbit/s serial PECL or CML electrical data into serial optical data compliant with the 1G BASE standard. An open collector compatible Transmit Disable (Tx\_Dis) is provided. A logic "1," or no connection on this pin will disable the laser from transmitting. A logic "0" on this pin provides normal operation. The transmitter has an internal automatic power control loop (APC) to ensure constant optical power output across supply voltage and temperature variations. An open collector compatible Transmit Fault (Tx\_Fault) is provided. TX\_Fault is a module output contacts that when high, indicates that the module transmitter has detected a fault condition related to laser operation or safety. The TX\_Fault output contact is an open drain/collector and shall be pulled up to the Vcc\_Host in the host with a resistor in the range 4.7-10 k $\Omega$ . TX\_Disable is a module input contact. When TX\_Disable is asserted high or left open, the SFP module transmitter output shall be turned off. This contact shall be pulled up to VccT with a 4.7 k $\Omega$  to 10 k $\Omega$  resistor.




**PAGE 8/11** 

TITLE	DOC No.	DTRX-180017
	<b>REVISION:</b>	<b>AUTHORIZED BY:</b>
1G SFP SX Transceiver	04	Mike Sun
	DATE:	CLASSIFICATION:
	2022.05.26	Optical Transceiver

#### Receiver Section

The receiver converts 1.25Gbit/s serial optical data into serial PECL/CML electrical data. An open collector compatible Loss of Signal is provided. Rx\_LOS when high indicates an optical signal level below that specified in the relevant standard. The Rx\_LOS contact is an open drain/collector output and shall be pulled up to Vcc\_Host in the host with a resistor in the range 4.7-10 k $\Omega$ , or with an active termination. Power supply filtering is recommended for both the transmitter and receiver. The Rx\_LOS signal is intended as a preliminary indication to the system in which the SFP is installed that the received signal strength is below the specified range. Such an indication typically points to non-installed cables, broken cables, or a disabled, failing or a powered off transmitter at the far end of the cable.



Recommended Interface Circuit



#### **PAGE 9/11**

TITLE	DOC No.	DTRX-180017
	<b>REVISION:</b>	AUTHORIZED BY:
1G SFP SX Transceiver	04	Mike Sun
	DATE:	CLASSIFICATION:
	2022.05.26	Optical Transceiver

### 7. <u>Digital Diagnostic Memory Map</u>

2 wire address 1010000X (A0h)

Serial ID Defined by SFP MSA (96 bytes)

Vendor Specific (32 bytes)

Reserved in SFP MSA (128 bytes)

2 wire address 1010001X (A2h)

_	
0	Alarm and Warning
55	Thresholds (56 bytes)
55	Cal Constants
0.5	(40 bytes)
95	Real Time Diagnostic
110	Interface (24 bytes)
119 127	Vendor Specific (8 bytes)
247	User Writable EEPROM (120 bytes)
	Vendor Specific (8 bytes)
255	

Addr.	Field Size	Name of Field	Hex	Description
	(Bytes)			
0	1	Identifer	03	SFP
1	10	Ext. Identifier	04	SFP function is defined by serial ID only
2	1	Connector	07	LC Connector
3-10	8	Transceiver	10 00 00 00 20 40 0C 54	Transceiver Codes
11	1	Encoding	03	NRZ
12	1	BR, Nominal	01	1Gb/s
13	1	Rate Identifier	00	Unspecified
14	1	Length (9um) km	00	Transceiver transmit distance



#### **PAGE 10/11**

TITLE	DOC No.	DTRX-180017
	<b>REVISION:</b>	<b>AUTHORIZED BY:</b>
1G SFP SX Transceiver	04	Mike Sun
	DATE:	CLASSIFICATION:
	2022.05.26	Optical Transceiver

15	1	Length (9um) 100m	00	Transceiver transmit distance	
16	1	Length (50um OM2)	00		
17	1	Length (62.5um) 10m	00	Transceiver transmit distance	
18	1	Length (Copper)	00	Not compliant	
19	1	Length (50um OM3)	00		
20-35	16	Vendor name	59 69 20 56 61 6C 6C 65	"JPC" Vendor Name(ASCII)	
20-35	10	vendor name	79 20 20 20 20 20 20 20	SFC Vendor Name(ASCII)	
36	1	Reserved	00		
37-39	3	Vendor OUI	00 00 00		
40-55	16	Vendor PN	59 56 30 31 2D 50 30 32	Part No.(ASCII)	
40-55	10	vendor FN	20 20 20 20 20 20 20 20	Fait No.(ASCII)	
56-59	4	Vendor rev	31 2E 30 20	"1.0" (ASCII)	
60-61	2	Wavelength	03 52	Transceiver wavelength	
62	1	Reserved	00		
63	1	CC_BASE	87	Check code for Base ID Fields	
64-65	2	Ontions	00.14	TX_DISABLE, TX_FAULT and	
64-65	2	Options	Options 00 1A		
66	1	BR,MAX	00	Not Specified	
67	1	BR,MIN	00	Not Specified	
68-83	16	Vendor SN	SN(Variable)	Serial Number of transceiver(ASCII).	
84-91	8	Date code	DC(Variable)	Manufactory Date Code.	
		Diagnostic Monitoring		Digital diagnostic monitoring implemente	
92	1	Туре	68	"Internally calibrated" is implemented	



### **PAGE 11/11**

TITLE	DOC No.	DTRX-180017
	<b>REVISION:</b>	<b>AUTHORIZED BY:</b>
1G SFP SX Transceiver	04	Mike Sun
	DATE:	CLASSIFICATION:
	2022.05.26	Optical Transceiver

93	1	Enhanced Options	F0	Optional Alarm/Warning flags implemented for all monitored quantities, Optional Soft TX_Disable control and monitoring implemented, Optional Soft TX_FAULT monitoring implemented, Optional Soft RX_LOS monitoring implemented
94	1	SFF_8472 Compliance	04	Includes functionality described in  Rev10.4 SFF-8472
95	1	CC_EXT	CS(Variable)	Check sum for Extended ID Field.
96-127	32	Vendor Specific	Read only	Depends on customer information Filled by zero
128-255	128	Reserved	Read only	Filled by zero

## 8. Modification History

Rev.	Comments	Date	Originator	Approval
01	Preliminary Draft	2017.11.26	Mike Sun	Ray_Yang
02	Revise Part Number	2018.05.10	Mike Sun	Ray Yang
03	Add Certificate	2020.11.6	Mike Sun	Ray_Yang
04	Modify Receiver Sensitivity	2022.05.26	Albert	Mike Sun